


# **Polarization Maintaining Optical Isolator 1950nm**

The 1950nm (2 micron,  $2\mu$ m) Polarization Maintaining (PM) Optical Fiber Isolator is an in-line miro-optic component allows light to be transmitted only in the forward direction while blocking the backward transmittion. It's built with PM Panda fiber and designed to maintain the polarization of the input light with high extinction ratio. The PM isolators are commonly used to protect lasers or amplifiers against back-reflected light. Dual stage isolator means two singe stage isolators are packaged into one compact housing. It's ideal for eye safe  $2\mu$ m fiber laser systems.



### **Features**

High Isolation
High Extinction Ratio
Telcordia Test Compliant
High Power Available upon Request

### **Applications**

Fiber Amplifier Fiber Laser Fiber Sensor Instrumentations

### **Performance Specification**

Parameter	V	Unit			
Center Wavelength	1950 or	nm			
Bandwidth		nm			
Stage	Single Stage	Dule Stage			
Min. Isolation at 23°C	18	32	dB		
Typ. Insertion Loss at 23℃	0.8	1.0	dB		
Max. Insertion Loss at -5 to 50°C	1.2	1.4	dB		
Min. Extinction Ratio for Fast Axis Blocked	d Type	18	dB		
Min. Extinction Ratio for Both Axis Workin	д Туре	20	dB		
Min. Return Loss		50	dB		
Max. Optical Power (Continuous Wave	300 (higher power	mW			
Max. Tensile Load		5	N		
Fiber Type	PM 1550 Panda Fiber on Input & Output Port				
Operating Temperature	-5	to +50	$^{\circ}\mathbb{C}$		
Storage Temperature	-40	to +85	$^{\circ}$ C		
Package Dimension	Ф5	.5×L35	mm		

#### Note

## **Ordering Information**

#### PMI-AAAA-B-C-DD-EE-F

AAAA	В	С	DD	EE	F
Wavelength	Stage	Fiber Jacket	Fiber Length	Connector	Working Axis
1950 - 1950nm	S - Single Stage	B - 250um Bare	05 - 0.5m	NE - None	F - Fast Axis
SSSS - Specify D - Dual Stage	D - Dual Stage	Fiber	08 - 0.8m	FA - FC/APC	Blocked
		L - 900um Loose	10 - 1.0m	FP - FC/PC	B - Both Axis
		Tube	15 - 1.5m	SA - SC/APC	Operating
			SS - Specify	SP - SC/PC	
				LA- LC/APC	
				LP - LC/PC	
				SS - Specify	

<sup>\*</sup> For devices with connectors, IL will be 0.3dB higher, RL will be 5dB lower and ER will be 2dB lower.

<sup>\*</sup> The PM fiber and the connector key are aligned to the slow axis.